Wiring Colour Code Table

Many British designed vehicles use colour coded cables to assist in identifying the various circuits in use. This is an extract from BS-AU7a 1983 Colour Code for Vehicle Wiring, from the British Standards Institution, 2 Park St., London W1A 2BS.

(Note that these colour codes may not apply directly to older cars. For example, the wipers on cars up to 1980 (at least) are not on a separate fuse circuit, so they are not orange, but green. Check the schematic for your car to be certain.)

wire colour abbreviations are as follows

B= Black	N=Brown	R=Red	O=Orange	Y=Yellow
G=Green	U=Blue	P=Purple	LG=Light Green	K=Pink
S=Slate	W=White			

MAIN TRACER PURPOSE

Black		All earth connections
Black	Brown	Tachometer generator to tachometer
Black	Blue	Tachometer generator to tachometer
Black	Red	Electric or electronic speedometer to sensor
Black	Purple	Tempreature switch to warning light
Black	Green	Relay to radiator fan motor
Black	Light green	Vacuum brake switch or brake differential pressure valve to warning light and/or buzzer
Black	White	Brake fluid level warning light to switch and handbrake swith, or radio to speakers
Black	Yellow	Electric speedometer
Black	Orange	Radiator fan motor to thermal switch
MAIN	TRACER	PURPOSE
Blue		Lighting switch (head) to dip switch
Blue	Brown	Headlamp relay to headlamp fuse
Blue	Red	Dip switch to headlamp dip beam fuse
		Fuse to right-hand dip headlamp
Blue	Light green	Headlamp wiper motor to headlamp wash pump motor
Blue	White	a) Dip switch to headlamp main beam fuse
		b)Headlamp flasher to main beam fuse
		c)Dip switch main beam warning light
		d)Dip switch to long-range driving light switch
Blue		-, p
	Yellow	Long-range driving light switch to lamp
Blue	Black	Long-range driving light switch to lamp Fuse to right-hand main headlamp
		Long-range driving light switch to lamp Fuse to right-hand main headlamp Fuse to left-hand dip headlamp
Blue	Black	Long-range driving light switch to lamp Fuse to right-hand main headlamp

MAIN TRACER PURPOSE

Brown Main battery lead

Brown Blue Control box (compensated voltage control only) to ignition switch and lighting

switch (feed)

Brown Red Compression ignition starting aid to switch

Main battery feed to double pole ignition switch

Brown Purple Alternator regulator feed
Brown Green Dynamo 'F' to controlboxl 'F'

Alternator field 'F' to control box 'F'

Brown White Ammeter to control box

Ammeter to main alternator terminal

Brown Yellow Alternator to 'no charge' warning light

Brown Black Alternator battery sensing lead

Brown Slate Starter relay contact to starter solenoid

Brown Orange Fuel shut-off (diesel stop)

MAIN TRACER PURPOSE

Green Accessories fuesed via ignition switch

Green Brown Switch to reverse lamp

Gree Blue Water temperature gauge to temperature unit

Green Red Direction indicator switch to left-hand flasher lamps

Green Purple Stop lamp switch to stop lamps, or stop lamp switch to lamp failure unit

Green Light Hazard flasher unit to hazard pilot lamp or lamp failure unit to stop lamp

green bulbs

Green White Direction indicator switch to right hand flasher lamps

Green Yellow Heater motor to switch single speed (or to 'slow' on tow- or three-speed

motor)

Green Black Fuel gauge to fuel tank unit or changeover switch or voltage stabilizer to tank

units

Green Pink Fuse to flasher unit

Green Slate a) Heater motor to switch ('fast' on two- or three-speed motor)

b)Coolant level unit to warning light

Green Orange Low fuel level switch to warning light

MAIN TRACER PURPOSE

Light green Instrument voltage stabilizer to instruments

Light Brown Flasher switch to flasher unit

green Flowin Flasher switch to hasher unit

Light green a)Flasher switch to left-hand flasher warning light

b)Coolant level sensor to control unit c)Test switch to coolan level control unit

Light Red Fuel tank changeover switch to right-hand tank unit or entry and exit door

green closed switch to door actuator

Light green Purple Flasher unit to flasher warning light

Light Green Start inhibitor relay to change speed switch; or switch to heater blower motor

green second speed on three-speed unit

Light green	White	Low air pressure switch to buzzer and warning light
Light green	Yellow	Flasher switch to right-hand warning light; or differential lock switch to differential lock warning light
Light green	Black	Front screen jet switch to screen jet motor
Light green	Slate	Fuel tank changeover switch to left-hand tank unit; or entry and exit door open switch to door actuator
Light green	Orange	Rear window wash switch to wash pump; or cab lock-down switch to warning light

MAIN	TRACER	PURPOSE

Orange	Wiper circuits fused via ignition switch
Orange Blue	Switch to front screen wiper motor first speed timer or intermittend unit
Orange Green	Switch to front screen wiper motor second speed
Orange Black	Switch to front screen wiper motor parking cicuit, timer or intermittent unit
Orange Purple	Timer or intermittent unit to motor parking circuit
Orange White	Timer or intermittent unit to motor parking circuit
Orange Yellow	Switch to headlamp or rear window wiper motor feed, timer or relay coil
Orange Light green	Switch to headlamp or rear window wiper motor parking circuit timer or relay coil
Orange Pink	Timer or relay to headlamp or rear window wiper motor feed
Orange Slate	Timer or relay to headlamp or rear window wiper motor parking circuit
Pink white	Ballast terminal to ignition distributor

MAIN TRACER PURPOSE

Purple		Accessories fed direct from battery via fuse
Purple	Brown	Horn fuse to horn relay when horn is fused separately
Purple	Blue	Fuse to heated rear window relay or switch and warning light
Purple	Red	Switches to map light, under bonnet light, glove box light and boot lamp when fed direct from battery fuse
Purple	Green	Fuse to hazard flasher
Purple	Light green	Fuse to relay for screen demist
Purple	White	Interior lights to switch (subsidiary circuit door safety lights to switch)
Purple	Yellow	Horn to horn relay
Purple	Black	Horn to horn relay to horn push
Purple	Pink	Rear heated window to switch or relay
Purple	Slate	Aerial lift motor to switch up
Purple	Orange	Aerial lift motor to switch down

MAIN TRACER PURPOSE

Red		Main feed to all circuits mastered by sidelamp switch
Red	Brown	Rear fog guard switch to lamps
Red	Blue	Front fog lamp fuse to fog lamp switch
Red	Purple	Switches to map light, under bonnet light, glove box light and boot lamp when sidelamp circuit fed
Red	Green	Bulb failure unit to right-hand-side and rear lamps
Red	White	a)Sidelamp fuse to right-hand side and rear lamps

b)Sidelamp fuse to panel light rheostat c)Fuse to panel light switch or rheostat

d) Fuse to fibre optic source

Red Yellow Fog lamp switch to fog lamp or front fog fuse to fog lamps

Red Blakc Left-hand, sidelamp fuse to side and tail lamps and number plate illumination

Red Pink Sidelamp fuse to lighting relay

Red Slate Lamp failure unit to lef-hand side and tail lamps

Red Orange Fusebox to rear fog guard switch

Slate Window lift main lead

MAIN TRACER PURPOSE

White Ignition switch or starter solenoid to ballast resistor

White Brown Oil pressure switch to warning light or gauge, or starter relay to oil pressure

switch

White Blue Choke switch to choke solenoid (unfused) and/or choke to switch to warning

light, or electronic ignition distributor to drive resistor

White Red Starter switch to starter solenoid or inhibitor switch or starter relay or ignition

(start position) to bulb failure unit

White Purple Fuel pump no 1 or right-hand to changeover switch
White Green Fuel pump no 2 or left-hand to changeover switch

White Light Start switch to starter interlock or oil pressure switch to fuel pump or start

green inhibitor switch to starter relay or solenoid

White Yellow Ballast resistor to coil or starter solenoid to coil

White Black Ignition coil contact breaker to distributor contact breaker, or distributor side

of coil to voltage impulse tachometer

White Pink Ignition switch to radio fuse

White Slate Current tachometer to ignition coil
White Orange Hazard warning lead to switch

Yellow a) Overdrive

Purple Overdrive Solenoid
White Overdrive Manual Switch
Red Overdrive Gear Switch

b) Petrol injection

c)Door locks

d)Gear selector switch to start

Chris Kantarjiev of the Dimebank Garage